

Tuning Instructions for TECHNOSAT /SUPERNET/GLOBALSAT

1. Press "Menu" on your remote control
2. Press right arrow "▶" to move cursor to "Installation"
3. Press down "▼" to highlight to "Manual Search" and press "OK"
4. Press 0000 in response to "Please input password to enter this menu"
5. "Manual Search Menu" opens up
6. Press down "▼" to go to TP
7. Change the TP by pressing the right arrow▶ to any other TP where the Trans Freq is "12545"

If number is missing in the frequency list then follow the steps A, B and C
8. Press down "▼" to move cursor to "Trans Freq"
9. Should be 12545
10. Press down "▼" to move cursor to "Symbol Rate" should be 22500
11. Press down "▼" to move cursor to "Polarisation" should be "Vertical"
12. Press down "▼" to move cursor to "Network search" should be "ON". If it is off then press "▶" and change to "ON"
13. Press down "▼" till the end and then right arrow "" to move cursor to "Save" and press "OK"
14. Curser will go back to Satellite name "Optus B3"
15. Press down "▼" to highlight "Search TP" at bottom of page and press "OK"
16. It will ask for Search Mode .Highlight "All" and press "OK"
17. "Searching programs please wait a while "will come up. Once channels are tuned, a complete TV program window will appear.
18. Press "EXIT" button to get out of the main menu.
19. Change channels till you come to the Zee Punjabi

- A) Look for "NEW TP" and press "▼" and press the numbers 12706
- B) Press "▼" to go to Symbol rate and press the numbers 22500
- C) Press "▼" to go to Polarisation and press "▶" and change to "Vertical"