

# Tuning Instructions for TECHNOSAT /SUPERNET/GLOBALSAT

1. Press "Menu" on your remote control
  2. Press right arrow "▶" to move cursor to "Installation"
  3. Press down "▼" to highlight to "Manual Search" and press "OK"
  4. Press 0000 in response to "Please input password to enter this menu"
  5. "Manual Search Menu" opens up
  6. Press down "▼" to go to TP
  7. Change the TP by pressing the right arrow▶ to TP 5 or any other TP where the Frequency is 12706  
If number is missing in the frequency list then follow the steps A, B and C
  8. Press down "▼" to move cursor to "Trans Freq"
  9. Should be 12706
  10. Press down "▼" to move cursor to "Symbol Rate" should be 22500
  11. Press down "▼" to move cursor to "Polarisation" should be "Vertical"
  12. Press down "▼" to move cursor to "Network search" should be "ON". If it is off then press "▶" and change to "ON"
  13. Press down "▼" till the end and then right arrow "" to move cursor to "Save" and press "OK"
  14. Curser will go back to Satellite name "Optus B3"
  15. Press down "▼" to highlight "Search TP" at bottom of page and press "OK"
  16. It will ask for Search Mode .Highlight "All" and press "OK"
  17. "Searching programs please wait a while" will come up. Once channels are tuned, a complete TV program window will appear.
  18. Press "EXIT" button to get out of the main menu.
  19. Change channels till you come to the Colors channels
- A) Look for "NEW TP" and press "▼" and press the numbers 12706  
B) Press "▼" to go to Symbol rate and press the numbers 22500  
C) Press "▼" to go to Polarisation and press "▶" and change to "Vertical"

Please continue form step 12