

Tuning Instructions for ADB

1. Press "Menu" button on your remote control
2. Press down "▼" to highlight "Advanced Options" and press "OK"
3. Press down "▼" to highlight "Change Dish Installation" and press "OK"
4. Press 9949 (PIN code for installation)
5. Press down "▼" to "Change Manual Tuning Parameters" and press "OK"
6. Press down "▼" to "Home Network" and press "OK"
7. Change the Signal source to "Enabled" by pressing the "▶" arrow key
8. Press down "▼" to highlight "Frequency"
9. Press left "←" to delete all digits
10. Press "12545" from the remote
11. Press down "▼" to highlight "Symbol Rate" It should be 22500. If not, press "◀", to delete all numbers and type in 22500
12. Polarisation –Vertical, FEC-3/4
13. Network status should be 'ON'
14. Press "OK"
15. Press "EXIT" from the "Change Network Settings" screen to come to "Change Dish Installation" menu
16. Press down "▼" to "Tune DSD" and press "OK"
17. Wait while service scan takes place (approx 1 minute)
18. Change channels (scroll up channels) till you come to the Zee Punjabi