

Dreamax

Tuning Instructions

1. Press Menu
2. Press down arrow key Go to INSTALLATION
3. Press the right arrow and go to ANTENNA SETUP
4. Press OK and enter PIN NUMBER: 0000
5. Press OK on SAT NAME and from the list select OPTUS-B3/ Optus D2
6. Next Press OK on LNB Type and from the list select 11300 / 10700.
If not then, highlight any number in LNB Type and press 'OK'.
From the drop down list select the option 'User Define' and press OK
then press the numbers from the remote 10700.
7. LNB Power should be 13/ 18. If not press the right arrow and look for "13/18".
8. 22KHz should be AUTO . If not press the right arrow and look for "AUTO"
9. LNB Dish should be FIXED. If not press the right arrow and look for "FIXED"
10. DISC EqC should be OFF . If not then press the right arrow and look for "OFF"
11. Press BLUE button (Pause) on remote control to Save & Exit
12. Go to Manual Scan
13. SAT NAME should be OPTUS-B3 / Optus D2 (If not then repeat above steps)
14. Highlight TP Frequency Press right arrow key and look for the number 12706 .
If not then Press the Green button (SOUND) . It will ask for Add, Modify, Delete. Press OK on Add.
Press the numbers 12706 from your remote . Press down arrow key highlight Polarisation change to "Vertical"
and press the down arrow key Highlight Symbol rate and press the numbers 22500 from the remote.
Follow Step 17 now.
15. Polarisation should be Vertical (if it is horizontal, press right arrow key and make it vertical)
16. Symbol Rate should be 22500
17. Scan Mode should be All
18. Network Search should be ON (if it is off, press right arrow key and make it on)
19. Check Level and Quality should be GREEN in Colour
20. Press Red button on remote control (LANG) for scanning the channels.
21. "Please wait to save data" will appear. Press OK
22. Press Exit button thrice to go out of all the menus and now look for the Zoom

